

Remote counters 3AM16C

This is our basic 4 digit LCD counter and switch in a neat ABS box. Termination is by 3 wires to a screwless loudspeaker connection block. There is no logic interface and therefore any A3 counting must be done by a double pulse from the copier it is attached to.



Technical Specification

Supply

1.5volt DC from a singlr AA cell. [up to 7 years life]

Interface control lines used

Count, 0V ground,m/c enable(0v with switch ON)

Operating distances

Wired version up to 30 metres .,

Counter Digit size

4 digit LCD no backlight 10mm high

Overall Dimensions

120mmwide X 64mmhigh X 75mmdeep (includes connector and switch).

Supplied cable

None

Compatibility

Will operate with any copier that gives a low count pulse and requires a 0v signal to enable the operation of the machine.

Please contact for further information.

3AM UK Ltd.
07774 896004
alec.bushill@3am.uk.net

7,Farm Close,Lyne, Surrey.KT16 0AS. England